
# **WOHLER AMP1A-LP4S**

## Compact, High Quality Analog Self-Powered Speaker System - 4 Stereo Channels





## Features:

Full Fidelity Audio Monitoring in only IU of rack space
8 Balanced Analog Inputs (4 Stereo, Select I)
Balanced Analog Output of Selected Stereo Source
Powerful 98dB SPL at 2 feet (0.6m)
Two IO Segment Tri-Color Level Meters Displaying VU or PPM
Premium Quality Drivers & Power Amplifiers
Extended Frequency Response and Low Distortion
Focused Sound, Reduces Adjacent Bay Crosstalk
Audible Indication of Phase/Polarity Problems
Innovative LED Display of Phase/Polarity Relationships
Thorough Magnetic Shielding for Placement next to Video Monitors
Headphone Jack, Mutes Speakers
Blowout Proof Speakers
Quick and Simple Installation

The AMPIA-LP4S provides self-powered, full-fidelity stereo audio monitoring in the smallest rack space possible. A front panel switch allows the operator to select one stereo source for monitoring & output from up to 4 stereo analog inputs (8 channels). The AMPIA-LP4S features two 10 segment LED level meters showing VU or PPM for accurate level-metering. This unit contains four high performance transducers driven by three power amplifiers: one amplifier/driver combination handles midrange and high frequency information in stereo, while the second handles summed low frequency information below the 500 Hz crossover point.

The unique design provides optimally focused sound for operators in an Ultra Near Field (I to 3 ft.) working environment and offers performance comparable to that of many separate monitor pairs, yet does so without the installation hassles, awkward speaker placements and "added-on" look. This provides for a higher SPL for the operator while reducing overall ambient sound and adjacent bay crosstalk.


Extended HF response reveals potential problems with audio whine or hiss and electronic rather than acoustic cancellation of bass frequencies provides positive audible detection of out-of-phase (reversed polarity) audio feeds. A headphone jack is provided on the front panel, usage automatically mutes the speakers. The front panel features an innovative LED Display of Phase/Polarity Relationships. Output limiter circuits are incorporated to protect the speakers, and extensive magnetic shielding allows placement immediately adjacent to video monitors with no color impurities.

The AMPIA-LP4S is ideally suited for use in VTR bays, mobile production vehicles, teleconferencing installations, multimedia systems, satellite link and cable TV facilities, and on-air radio studios. Built and rigorously tested in the USA, the AMPIA-LP4S is backed by a strong warranty and a "Satisfaction Guaranteed" return policy.











## **WOHLER AMP1A-LP4S**

### Compact, High Quality Analog Self-Powered Speaker System - 4 Stereo Channels

## Rear Panel:



#### Right Channel HEADPHONE OUTPUT Left Speaker Left Input (Chan. A) Analog Switch Headphone Amp Level Metering Left Left Analog Amp Woofer Right Phase Ind. Right Left (Chan. A) (Chan. B) Volume Balance Right Input · · (Chan. B) 1234 Right Speaker Output of Fast O O Fast In Selected Source Power Indication Phase Indication Channel Input Select Switch (ISS) (Channel 1 Thru 4) Universal Power Supp y

Specifications:
Input
Output
Level meters
Level meter scale +3 to -20 dB
Level meter threshold6, 0, +4, +8 dBv: DIP switch selectable
Level meter dynamics
Midscale resolution
Analog input impedance>40 kOhms balanced
Peak acoustic output @ 2 feet98dB SPL
Frequency response (1/6 octave)80Hz - 20kHz (±5dB) (-10dB @ 50Hz, 22kHz)
Power output
Electrical distortion < 0.15% at any level below limit threshold
Acoustic distortion
Hum and noise better than -68dB below full output
Magnetic shielding
Power consumption (AVG. MAX.)30W
Dimensions (HxWxD)
Weight (approx.)
Power supply

All specifications are subject to improvement



www.i-techcompany.com Toll free:1-888-483-2418 USA:1-510-429-9288 Fax:1-510-372-2736