WOHLER VMQ-4

Analog Audio Monitor with 4 Simultaneous Discrete Channels



Features-

Monitoring of Four Discrete Audio Channels in One Unit Only One Rack Space High Dedicated Input for each Output Channel Powerful 94dB SPL at 2 feet (0.6m) 4 Balanced Analog Inputs

Signal Present LED on each Channel Input

Mute Button and LED for each Channel

Thorough Magnetic Shielding for Placement next to Video Monitors

Headphone Jack, Mutes Speakers

Blowout-Proof Speakers

Lightweight and Shallow-Depth Chassis

Internal Universal AC Mains Power Supply

Quick and Simple Installation

Also Available, an AES/EBU Version (VMQ-2D) and an SDI Version (VMQ-SDI)

The VMO-4 audio monitor from Wohler Technologies offers voice quality confidence monitoring of up to 4 analog channels simultaneously. The VMQ-4 only requires a compact IU of rackspace and is available at a very cost effective brice.

Because each channel has its own dedicated power amplifier and speaker, the audio sources remain completely separate from input to output. When listening within "Ultra Near Field" distances of 1 to 3 feet, these discrete speaker outputs provide enhanced source distinction when compared to designs with four inputs mixed into a single output.

Each channel has an LED which illuminates when a signal is present at the input allowing the operator to easily determine at a glance which channels are currently active, very helpful when quick volume adjustments are required. Separate mute buttons are provided for each channel; these together with an LED that indicates channel muting allow an operator to quickly mute one or more channels. A stereo headphone jack has channels I and 2 summed on the left side, and channels 3 and 4 on the right side.

The VMQ-4 is completely magnetically shielded to allow interference-free operation immediately adjacent to all CRT video monitors. The lighter weight and shallower-depth chassis compared to similar-type units, make it ideal for use in portable and mobile vehicle applications.




1-510-372-2736

Fax:







₩Wohler

WOHLER VMQ-4

Analog Audio Monitor with 4 Simultaneous Discrete Channels

Rear Panel:



IC8 (4 PST) Speaker AMP 1 Summing Channel 1 Input HEADPHONE OUTPUT Volume Speaker AMP 2 Input Channels 1-4 on Phoenix Connectors (also available as ŶVolume Headphone an optional extra: XLR Connectors) Summing AMP Channel 3 Input Speaker AMP 3 Channel 4 Input Speaker AMP 4 24VDC To All Circuits (CE Approved)

Specifications:
Input
Analog input impedance>100 kOhms balanced
Input level for full output (volume full on)
Hum and noise better than -70 dB below full output
Acoustic frequency response 300 Hz to 16 kHz (± 9dB)
Peak acoustic output @ 2 feet 94dB SPL
Electrical distortion < 0.2% at any level below limit threshold
Magnetic shielding < I gauss any adjacent surface
Analog input connectors phoenix, XLR available as an optional extra
Dimensions (HxWxD)
Weight
Power supply
Power consumption

All specifications are subject to improvement

