

AD Board Part no.: DAY003-HDMI RS232

RS232 Remote Control via Command Code

RS232 PROTOCOL

Start(0x69)---->Command(0x--)->Id(0x--)->End

MENU,	0x69	0x97	0x01	0x00
LEFT,	0x69	0xA7	0x01	0x00
RIGHT,	0x69	0xB7	0x01	0x00
EXIT,	0x69	0xD6	0x01	0x00
HDMI,	0x69	0x67	0x01	0x00
VGA,	0x69	0xDA	0x01	0x00
DVI,	0x69	0xDB	0x01	0x00
Power_On,	0x69	0xD1	0x01	0x00
Power_Off,	0x69	0xD0	0x01	0x00

LEFT and **RIGHT** button are also UP and DOWN button in our OSD controller board.

UP button is the hot key control brightness +

DOWN button is the hot key control brightness -

